



**Table C: Rated Lighting System Wattage Table**

<b>BX</b>	Biax /Twin Tube Lamp	<b>EE</b>	Energy-Efficient Lamp	<b>STD</b>	Standard Ballast or Lamp
<b>HW</b>	Hard Wire Fixture	<b>ELIG</b>	Electronic Ballast	<b>HO</b>	High Output Lamp
<b>EEMAG</b>	Energy-Efficient Magnetic Balt.	<b>LPF</b>	Low Power Ballast Factor < 0.80	<b>VHO</b>	Very High Output Lamp
<b>HP</b>	High Performance T8 Systems	<b>HPF</b>	High Power Ballast Factor > 1.0	<b>RW</b>	Reduced Wattage T8 Systems

**Existing Fixture Codes**

Incandescent Lamps		
<u>Device Code</u>	<u>Device Description</u>	<u>Rated Watts</u>
1I0015	15W INC	15
1I0020	20W INC	20
1I0025	25W INC	25
1I0034	34W INC	34
1I0036	36W INC	36
1I0040	40W INC	40
1I0042	42W INC	42
1I0045	45W INC	45
1I0050	50W INC	50
1I0052	52W INC	52
1I0054	54W INC	54
1I0055	55W INC	55
1I0060	60W INC	60
1I0065	65W INC	65
1I0067	67W INC	67
1I0069	69W INC	69
1I0072	72W INC	72
1I0075	75W INC	75
1I0080	80W INC	80
1I0085	85W INC	85
1I0090	90W INC	90
1I0093	93W INC	93
1I0100	100W INC	100
1I0120	120W INC	120
1I0125	125W INC	125
1I0135	135W INC	135
1I0150	150W INC	150
1I0200	200W INC	200
1I0300	300W INC	300
1I0448	448W INC	448
1I0500	500W INC	500
1I0750	750W INC	750

1I1000	1000W INC	1000
1I1500	1500W INC	1500

## 2011-2012 Lighting

<b>Low Voltage Halogen Fixture ( includes transformer)</b>		
<b>Device Code</b>	<b>Device Description</b>	<b>Rated Watts</b>
1R0020	20W LV HALOGEN FIXT	30
1R0025	25W LV HALOGEN FIXT	35
1R0035	35W LV HALOGEN FIXT	45
1R0042	42W LV HALOGEN FIXT	52
1R0050	50W LV HALOGEN FIXT	60
1R0065	65W LV HALOGEN FIXT	75
1R0075	75W LV HALOGEN FIXT	85

<b>Halogen/Quartz Lamps</b>		
1T0035	35W HALOGEN LAMP	35
1T0040	40W HALOGEN LAMP	40
1T0042	42W HALOGEN LAMP	42
1T0045	45W HALOGEN LAMP	45
1T0050	50W HALOGEN LAMP	50
1T0052	52W HALOGEN LAMP	52
1T0055	55W HALOGEN LAMP	55
1T0060	60W HALOGEN LAMP	60
1T0072	72W HALOGEN LAMP	72
1T0075	75W HALOGEN LAMP	75
1T0090	90W HALOGEN LAMP	90
1T0100	100W HALOGEN LAMP	100
1T0150	150W HALOGEN LAMP	150
1T0200	200W HALOGEN LAMP	200
1T0250	250W HALOGEN LAMP	250
1T0300	300W HALOGEN LAMP	300
1T0350	350W HALOGEN LAMP	350
1T0400	400W HALOGEN LAMP	400
1T0425	425W HALOGEN LAMP	425
1T0500	500W HALOGEN LAMP	500
1T0750	750W HALOGEN LAMP	750
1T0900	900W HALOGEN LAMP	900
1T1000	1000W HALOGEN LAMP	1000
1T1200	1200W HALOGEN LAMP	1200
1T1500	1500W HALOGEN LAMP	1500

## Existing Fixture Codes (cont.)

Mercury Vapor (MV)		
Device Code	Device Description	Rated Watts
1V0040S	40W MERCURY	50
1V0050S	50W MERCURY	75
1V0075S	75W MERCURY	95
1V0100S	100W MERCURY	120
1V0175S	175W MERCURY	205
1V0250S	250W MERCURY	290
1V0400S	400W MERCURY	455
1V0700S	700W MERCURY	775
1V1000S	1000W MERCURY	1075
2V0400S	2/400W MERCURY	880

Low Pressure Sodium (LPS)		
Device Code	Device Description	Rated Watts
1L0035S	35W LPS	60
1L0055S	55W LPS	85
1L0090S	90W LPS	130
1L0135S	135W LPS	180
1L0180S	180W LPS	230

High Pressure Sodium (HPS)		
Device Code	Device Description	Rated Watts
1H0035S	35W HPS	45
1H0050S	50W HPS	65
1H0070S	70W HPS	90
1H0100S	100W HPS	130
1H0150S	150W HPS	190
1H0200S	200W HPS	240
1H0225S	225W HPS	275
1H0250S	250W HPS	295
1H0310S	310W HPS	350
1H0360S	360W HPS	435
1H0400S	400W HPS	460
1H0600S	600W HPS	675
1H0750S	750W HPS	835
1H1000S	1000W HPS	1085

Metal Halide (MH)		
Device Code	Device Description	Rated Watts
1M0032S	32W METAL HALIDE	40
1M0050S	50W METAL HALIDE	65
1M0070S	70W METAL HALIDE	95
1M0100S	100W METAL HALIDE	120
1M0150S	150W METAL HALIDE	190
1M0175S	175W METAL HALIDE	205
1M0250S	250W METAL HALIDE	295
1M0360S	360W METAL HALIDE	430
1M0400S	400W METAL HALIDE	455
1M0750S	750W METAL HALIDE	825
1M1000S	1000W METAL HALIDE	1075
1M1500S	1500W METAL HALIDE	1615
1M1800S	1800W METAL HALIDE	1875

Two Foot T8, T12 and Biax Systems		
Device Code	Device Description	Rated Watts
1F20SSS	F20T12/HPF(1)	32
1F55BXE	1L2' F55BX/ELIG	56
1F80BXE	1L2' F80BXE/ELIG	90
2F17SSL	2L2' T8/ELIG LPF	27
2F17SSE	2L2' T8/ELIG	37
2F17SSM	2L2' T8/EEMAG	45
2F20SSS	F20T12/HPF(2)	56
2F40BXE	2L2' F40BX/ELIG	72
2F24HSS	2L2' HO/STD/STD	85
2F50BXE	2L2' F50BX/ELIG	108
2F55BXE	2L2'55BXE/ELIG	112
3F17SSE	3L2' T8/ELIG	53
3F17SSL	3L2' T8/ELIG LPF	39
3F20SSS	F20T12/HPF(3)	78
3F40BXE	3L2' F40BX/ELIG	102
3F50BXE	3L2' F50BX/ELIG	162
3F55BXE	3L2' F55BX/ELIG	168
4F17SSE	4L2' T8/ELIG	62
4F36BXE	4L2' F36BX/ELIG	148
4F40BXE	4L2' F40BX/ELIG	144
4F40BXH	4L 40W T5 (Std.) HPF	170
4F50BXE	4L2' F50BX/ELIG	216
4F55BXE	4L2' F55BX/ELIG	224
5F40BXE	5L2' F40BX/ELIG	190
5F50BXE	5L2' F50BX/ELIG	270
5F55BXE	5L2' F55BX/ELIG	280
6F36BXE	6L2' F36BX/ELIG	212
6F40BXE	6L2' F40BX/ELIG	204
6F50BXE	6L2' F50BX/ELIG	324
6F55BXE	6L2' F55BX/ELIG	336
8F36BXE	8L2' F36BX/ELIG	296
8F40BXE	8L2' F40BX/ELIG	288
8F50BXE	8L2' F50BX/ELIG	432
8F55BXE	8L2' F55BX/ELIG	448
9F36BXE	9L2' F36BX/ELIG	318
9F40BXE	9L2' F40BX/ELIG	306
9F50BXE	9L2' F50BX/ELIG	486
9F55BXE	9L2' F55BX/ELIG	504
12F40BE	12L2' F40BX/ELIG	408
12F50BE	12L2' F50BX/ELIG	648
12F55BE	12L2' F55BX/ELIG	672

Three Foot T8 Systems		
Device Code	Device Description	Rated Watts
1F25SSE	1L3'T8/ELIG	24
2F25SSE	2L3' T8/ELIG	47
3F25SSE	3L3'T8/ELIG	68
4F25SSE	4L3' T8/ELIG	88

# 2011-2012 Lighting

## Existing Fixture Codes (cont.)

Two Foot T8 Systems		
Device Code	Device Description	Rated Watts
1F17EEL	1L2' 17W T8EE/ELEE LPF	14
1F17EEE	1L2' 17W T8EE/ELEE	17
2F17EEL	2L2' 17W T8EE/ELEE LPF	26
2F17EEE	2L2' 17W T8EE/ELEE	29
3F17EEL	3L2' 17W T8EE/ELEE LPF	38
3F17EEE	3L2' 17W T8EE/ELEE	44

Three Foot T12 Systems		
Device Code	Device Description	Rated Watts
1F30SEM	1L3' EE/EEMAG	38
1F30SES	1L3' EE/STD	42
1F30SSS	1L3' STD/STD	46
2F25SSM	2L3' T8/EEMAG	65
2F30SEE	2L3' EE/ELIG	49
2F30SEM	2L3' EE/EEMAG	66
2F30SES	2L3' EE/STD	73
2F30SSS	2L3' STD/STD	80
3F30SES	3L3' EE/STD	127
3F30SSS	3L3' STD/STD	140

Four Foot F48 T12 Systems		
Device Code	Device Description	Rated Watts
1F48SES	1L4' F48T12EE/STD	50
1F48SSS	1L4' F48T12/STD	60
2F48SES	2L4' F48T12EE/STD	82
2F48SSS	2L4' F48T12/STD	102
3F48SES	3L4' F48T12EE/STD	132
3F48SSS	3L4' F48T12/STD	162
4F48SES	4L4' F48T12EE/STD	164
4F48SSS	4L4' F48T12/STD	204

Four Foot F48HO T12 Systems		
Device Code	Device Description	Rated Watts
1F48HES	1L4' F48HO/EE/STD	80
1F48HSS	1L4' F48HO/STD/STD	85
2F48HES	2L4' F48HO/EE/STD	135
2F48HSS	2L4' F48HO/STD/STD	145
3F48HES	3L4' F48HO/EE/STD	215
3F48HSS	3L4' F48HO/STD/STD	230
4F48HES	4L4' F48HO/EE/STD	270
4F48HSS	4L4' F48HO/STD/STD	290

Four Foot F48VHO T12 Systems		
Device Code	Device Description	Rated Watts
1F48VES	1L4' F48VHO/EE/STD	123
1F48VSS	1L4' F48VHO/STD/STD	138
2F48VES	2L4' F48VHO/EE/STD	210
2F48VSS	2L4' F48VHO/STD/STD	240
3F48VES	3L4' F48VHO/EE/STD	333
3F48VSS	3L4' F48VHO/STD/STD	378
4F48VES	4L4' F48VHO/EE/STD	420
4F48VSS	4L4' F48VHO/STD/STD	480

Four Foot T12 Systems		
Device Code	Device Description	Rated Watts
1F40SEE	1L4' EE/ELIG	38
1F40SEM	1L4' EE/EEMAG	40
1F40SES	1L4' EE/STD	50
1F40SSE	1L4' STD/ELIG	46
1F40SSM	1L4' STD/EEMAG	50
1F40SSS	1L4' STD/STD	57
2F40SEE	2L4' EE/ELIG	60
2F40SEM	2L4' EE/EEMAG	70
2F40SES	2L4' EE/STD	80
2F40SSE	2L4' STD/ELIG	72
2F40SSM	2L4' STD/EEMAG	86
2F40SSS	2L4' STD/STD	94
3F40SEE	3L4' EE/ELIG	90
3F40SEM	3L4' EE/EEMAG	110
3F40SES	3L4' EE/STD	130
3F40SSE	3L4' STD/ELIG	110
3F40SSM	3L4' STD/EEMAG	136
3F40SSS	3L4' STD/STD	151
4F40SEE	4L4' EE/ELIG	120
4F40SEM	4L4' EE/EEMAG	140
4F40SES	4L4' EE/STD	160
4F40SSE	4L4' STD/ELIG	144
4F40SSM	4L4' STD/EEMAG	172
4F40SSS	4L4' STD/STD	188
6F40SSS	6L4' STD/STD	282

Four Foot T8 Systems		
Device Code	Device Description	Rated Watts
1F32SSL	1L4 T8/ELIG LPF	26
1F32SSE	1L4' T8/ELIG	30
1F32SSM	1L4' T8/EEMAG	37
2F32SSL	2L4 T8/ELIG LPF	52
2F32SSE	2L4' T8/ELIG	60
2F32SSH	2L4' T8/ELIG HPF	78
2F32SSM	2L4' T8/EEMAG	70
3F32SSL	3L4 T8/ELIG LPF	76
3F32SSE	3L4' T8/ELIG	88
3F32SSH	3L4' T8/ELIG HPF	112
3F32SSM	3L4' T8/EEMAG	107
4F32SSL	4L4 T8/ELIG LPF	98
4F32SSE	4L4' T8/ELIG	112
4F32SSH	4L4' T8/ELIG HPF	156
4F32SSM	4L4' T8/EEMAG	140
5F32SSE	5L4' T8/ELIG	148
5F32SSH	5L4' T8/ELIG HPF	190
6F32SSE	6L4' T8/ELIG	174
8F32SSH	8L4' T8/ELIG HPF	312

# 2011-2012 Lighting

## Existing Fixture Codes (cont.)

### Four Foot Tandem-Wired T8 Systems

Device Code	Device Description	Rated Watts
2W32SSE	2L4' TW T8/ELIG	60
2W32SSH	2L4' TW T8/HPF	78
2W59SSE	2L8' TW T8/ELIG	109
2W59SSH	2L8' TW T8/ELIG	138
2W96SSE	2L8' TW EE/ELIG	120
2W96SSE	2L8' TW STD/ELIG	156
4W32SSL	4L4 DTWT8/ELIG LPF	98
4W32SSE	4L4' DTWT8/ELIG	112

### Five Foot T8 / T12 Systems

1F40HSE	1L5' HO/STD/ELIG	59
1F60HSM	1L5' HO/STD/EEMAG	90
2F40HSE	2L5' HO/STD/ELIG	123
2F40TSE	2L5'T8/ELIG	68
2F60HSM	2L5' HO/STD/EEMAG	178
3F40TSE	3L5'T8/ELIG	106

### Six Foot T 12 & T12 HO Systems

1F72SSM	1L6' STD/EEMAG	80
1F72SSS	1L6' STD/STD	95
1F72HSS	1L6' F72HO/STD/STD	113
2F72HSE	2L6'T8 HO/ELIG	160
2F72HSM	2L6' F72HO/STD/EEMAG	193
2F72HSS	2L6' F72HO/STD	195
2F72SSM	2L6' STD/EEMAG	135
2F72SSS	2L6' STD/STD	173

### Eight Foot T12 & T12 HO Systems

1F96SEE	1L8' EE/ELIG	60
1F96SSE	1L8' STD/ELIG	70
1F96SES	1L8' EE/STD	83
1F96SES	1L8' EE/ELIG	60
1F96SSS	1L8' STD/STD	100
1F96HES	1L8' HO/EE/STD	125
1F96HSS	1L8' HO/STD/STD	135
2F96SEE	2L8' EE/ELIG	109
2F96SEM	2L8' EE/EEMAG	123
2F96SSE	2L8' STD/ELIG	134
2F96SES	2L8' EE/STD	138
2F96SSM	2L8' EE/EEMAG	158
2F96SSS	2L8' STD/STD	173
3F96SSE	2L8' STD/ELIG	134
3F96SSS	3L8' EE/STD	221
3F96SSM	2L8' STD/STD	273
3F96HES	3L8' HO/EE/STD	352
3F96HSS	3L8' HO/STD/STD	392

### Eight Foot T12 & T12 HO Systems (cont.)

Device Code	Device Description	Rated Watts
4F96SEE	4L8' EE/ELIG	218
4F96SEM	4L8' EE/EEMAG	246
4F96SSE	4L8' STD/ELIG	268
4F96HEE	4L8' HO/EE/ELIG	340
4F96HEM	4L8' HO/EE/EEMAG	414
4F96HES	4L8' HO/EE/STD	454
4F96HSE	4L8' HO/STD/ELIG	390
4F96HSM	4L8' HO/STD/EEMAG	474
4F96HSS	4L8' HO/STD/STD	514

### Eight Foot T12 VHO Systems

1F96VES	1L8' VHO/EE/STD	200
1F96VSS	1L8' VHO/STD/STD	230
2F96VES	2L8' VHO/EE/STD	390
2F96VSS	2L8' VHO/STD/STD	450
3F96VES	3L8' VHO/EE/STD	590
3F96VSS	3L8' VHO/STD/STD	680
4F96VES	4L8' VHO/EE/STD	780
4F96VSS	4L8' VHO/STD/STD	900

### Eight Foot T8 Systems

1F59SSE	1L8' T8/ELIG	60
1F80SSE	1L8' T8 HO/ELIG	85
2F59SSL	2L8' T8/ELIG LPF	100
2F59SSE	2L8' T8/ELIG	109
2F80SSE	2L8' T8 HO/ELIG	160
1F96SEE	1L8' EE/ELIG	60
1F96SES	1L8' EE/STD	83
1F96SSE	1L8' STD/ELIG	70
1F96SSS	1L8' STD/STD	100
2F96SEE	2L8' EE/ELIG	109
2F96SEM	2L8' EE/EEMAG	123
2F96SSE	2L8' STD/ELIG	134
2F96SES	2L8' EE/STD	138
2F96SSM	2L8' STD/EEMAG	158
2F96SSS	2L8' STD/STD	173
4F96SSM	4L8' STD/EEMAG	316
4F96SSS	4L8' STD/STD	346

<b>BX</b>	Biax / Twin Tube Lamp	<b>EE</b>	Energy-Efficient Lamp
<b>HW</b>	Hard Wire Fixture	<b>ELIG</b>	Electronic Ballast
<b>HP</b>	High Performance T8 systems	<b>LPF</b>	Low Power Ballast Factor < 0.80
<b>RW</b>	Reduced Wattage T8 Systems	<b>HPF</b>	High Power Ballast Factor > 1.0

## Proposed Fixture Codes

CWA / Linear MH Lamp/Ballast		
Device Code	Device Description	Rated Watts
1M0100P	100W MH CWA	128
1M0100R	100W MH Linear	118
1M0150P	150W MH CWA	190
1M0150R	150W MH Linear	172
1M0175P	175W MH CWA	208
1M0175R	175W MH Linear	190
1M0200P	200W CWA	232
1M0200R	200W LINEAR	218
1M0250P	250W CWA	288
1M0250R	250W MH LINEAR	265
1M0300P	300W CWA	342
1M0300R	300W Linear	324
1M0320P	320W CWA	365
1M0320R	320W LINEAR	345
1M0350P	350W CWA	400
1M0350R	350W LINEAR	375
1M0400P	400W CWA	455
1M0400R	400W LINEAR	430
1M0450P	450W MH CWA	508
1M0450R	450W MH LINEAR	480
1M0750P	750W MH CWA	815
1M0750R	750W MH Linear	805
1M1000P	1000W CWA	1080

MH Track Lighting		
Device Code	Device Description	Rated Watts
1M0035E	35W MH SPOT	44
1M0070E	70W MH SPOT	80
1M0100E	100W MH SPOT	111

LED Exit Signs		
Device Code	Device Description	Rated Watts
1E0005C	0.5 WATT LED	0.5
1E0015	1.5 WATT LED	1.5
1E0002	2.0 WATT LED	2
1E0003	3.0 WATT LED	3
1E0005	5.0 WATT LED	5
1E0008	8.0 WATT LED	8
1E0105	10.5 WATT LED	10.5

Compact Fluorescents (CFL's)		
Device Code	Device Description	Rated Watts
1C0005S	5W COMPACT HW	7
1C0007S	7W COMPACT HW	9
1C0009S	9W COMPACT HW	11
1C0011S	11W COMPACT HW	13
1C0013S	13W COMPACT HW	15
1C0018E	18W COMPACT HW ELIG	20
1C0018S	18W COMPACT HW	20
1C0022S	22W COMPACT HW	24
1C0023E	1/23W COMPACT HW ELIG	25
1C0026E	26W COMPACT HW ELIG	28
1C0026S	26W COMPACT HW	28
1C0028S	28W COMPACT HW	30
1C0032S	32W CIRCLINE HW	34
1C0042E	1/42W COMPACT HW ELIG	48
1C0044S	44W CIRCLINE HW	46
1C0057E	1/57W COMPACT HW ELIG	65
1C2232S	22/32W CIRCLINE HW	58
1C2D10E	10W 2D COMPACT HW ELIG	12
1C2D16E	16W 2D COMPACT HW ELIG	18
1C2D21E	21W 2D COMPACT HW ELIG	22
1C2D28E	28W 2D COMPACT HW ELIG	28
1C2D38E	38W 2D COMP.HW ELIG	36
1C3240S	32/40W CIRCLINE HW	80
2C0005S	2/5W COMPACT HW	14
2C0007S	2/7W COMPACT HW	18
2C0009S	2/9W COMPACT HW	22
2C0011S	2/11W COMPACT HW	26
2C0013E	2/13W COMPACT HW ELIG	28
2C0013S	2/13W COMPACT HW	30
2C0018E	2/18W COMP. HW ELIG	40
2C0026E	2/26W COMP. HW ELIG	54
2C0032E	2'/32W COMPACT HW ELIG	68
2C0042E	2/42W COMPACT HW ELIG	100
3C0009S	3/9W COMPACT HW	33
3C0013S	3/13W COMPACT HW	45
3C0018E	3'/18W COMPACT HW ELIG	60
3C0026E	3/26W COMPACT HW ELIG	82

# 2011-2012 Lighting

## Proposed Fixture Codes (cont.)

Compact Fluorescents (CFL's) (cont.)		
3C0032E	3/32W COMPACT HW ELIG	114
3C0042E	3/42W COMPACT HW ELIG	141
4C0018E	4/18W COMPACT HW ELIG	80
4C0026E	4/26W COMPACT HW ELIG	108
4C0032E	4/32W COMPACT HW ELIG	152
4C0042E	4/42W COMPACT HW ELIG	188
6C0026E	6/26W COMPACT HW ELIG	162
6C0032E	6/32W COMPACT HW ELIG	228
6C0042E	6/42W COMPACT HW ELIG	282
8C0026E	8/26W COMPACT HW ELIG	216
8C0032E	8/32W COMPACT HW ELIG	304
8C0042E	8/42W COMPACT HW ELIG	376

Four Foot Tandem Wired T8 HP/RW Systems		
2W28EEL	2L4' TW T8EE/ELEE LPF	42
2W28EEE	2L4' TW T8EE/ELEE	48
3W28EEL	3L4' TW T8EE/ELEE LPF	63
3W28EEE	3L4' TW T8EE/ELEE	72
4W28EEL	4L4' TW T8EE/ELEE LPF	83
4W28EEE	4L4' TW T8EE/ELEE	94
3W32EEL	3L4' TW T8EE/ELEE LPF	72
3W32EEE	3L4' TW T8EE/ELEE	82
4W32EEL	4L4' TW T8EE/ELEE LPF	95
4W32EEE	4L4' TW T8EE/ELEE	107

Two Foot Biax Systems (long twin tube lamps)		
Device Code	Device Description	Rated Watts
1F55BXE	1L2' F55BX/ELIG	56
1F80BXE	1L2' F80BXE/ELIG	90
2F40BXE	2L2' F40BX/ELIG	72
2F50BXE	2L2' F50BX/ELIG	108
2F55BXE	2L2' F55BXE/ELIG	112
3F24HSE	3L4' T5HO/ELIG	80
3F40BXE	3L2' F40BX/ELIG	102
3F50BXE	3L2' F50BX/ELIG	162
3F55BXE	3L2' F55BX/ELIG	168
4F36BXE	4L2' F36BX/ELIG	148
4F40BXE	4L2' F40BX/ELIG	144
4F40BXH	4L 40W T5 (Std.) HPF	170
4F50BXE	4L2' F50BX/ELIG	216
4F55BXE	4L2' F55BX/ELIG	224
5F40BXE	5L2' F40BX/ELIG	190
5F50BXE	5L2' F50BX/ELIG	270
5F55BXE	5L2' F55BX/ELIG	280
6F36BXE	6L2' F36BX/ELIG	212
6F40BXE	6L2' F40BX/ELIG	204
6F50BXE	6L2' F50BX/ELIG	324
6F55BXE	6L2' F55BX/ELIG	336
8F36BXE	8L2' F36BX/ELIG	296
8F40BXE	8L2' F40BX/ELIG	288
8F50BXE	8L2' F50BX/ELIG	432
8F55BXE	8L2' F55BX/ELIG	448
9F36BXE	9L2' F36BX/ELIG	318
9F40BXE	9L2' F40BX/ELIG	306
9F50BXE	9L2' F50BX/ELIG	486
9F55BXE	9L2' F55BX/ELIG	504
12F40BE	12L2' F40BX/ELIG	408
12F50BE	12L2' F50BX/ELIG	648
12F55BE	12L2' F55BX/ELIG	672

Two Foot High Efficient T8 Systems		
Device Code	Device Description	Rated Watts
1F17ESL	1L2' 17W T8EE/ELEE LPF	14
1F17ESN	1L2' 17W T8EE/ELEE	17
1F17ESH	1L2' 17W T8EE/ELEE HPF	20
2F17ESL	2L2' 17W T8EE/ELEE LPF	27
2F17ESN	2L2' 17W T8EE/ELEE	32
2F17ESH	2L2' 17W T8EE/ELEE HPF	40
3F17ESL	3L2' 17W T8EE/ELEE LPF	39
3F17ESN	3L2' 17W T8EE/ELEE	46
3F17ESH	3L2' 17W T8EE/ELEE HPF	61

Three Foot High Efficient T8 Systems		
1F25ESL	1L3' 25W T8EE/ELEE LPB	21
1F25ESN	1L3' 25W T8EE/ELEE	24
1F25ESH	1L3' 25W T8EE/ELEE HPB	30
2F25ESL	2L3' 25W T8EE/ELEE LPB	40
2F25ESN	2L3' 25W T8EE/ELEE	45
2F25ESH	2L3' 25W T8EE/ELEE HPB	60
3F25ESL	3L3' 25W T8EE/ELEE LPB	58
3F25ESN	3L3' 25W T8EE/ELEE	67
3F25ESH	3L3' 25W T8EE/ELEE HPB	90

Electronic Metal Halide Lamps		
1M0150E	150W METAL HALIDE EB	160
1M0200E	200W METAL HALIDE EB	215
1M0250E	250W METAL HALIDE EB	270
1M0320E	320W METAL HALIDE EB	345
1M0350E	350W METAL HALIDE EB	375
1M0400E	400W METAL HALIDE EB	430
1M0450E	400W METAL HALIDE EB	480

# 2011-2012 Lighting

## Proposed Fixture Codes (cont.)

LED Lighting Fixtures		
<u>Device Code</u>	<u>Device Description</u>	<u>Rated Watts</u>
1L010	10 WATT LED	10
1L011	11 WATT LED	11
1L012	12 WATT LED	12
1L014	14 WATT LED	14
1L015	15 WATT LED	15
1L016	16 WATT LED	16
1L017	17 WATT LED	17
1L023	23 WATT LED	23
1L025	25 WATT LED	25
1L028	28 WATT LED	28
1L029	29 WATT LED	29
1L035	35 WATT LED	35
1L040	40 WATT LED	40
1L045	45 WATT LED	45
1L050	50 WATT LED	50
1L055	55 WATT LED	55
1L060	60 WATT LED	60
1L070	70 WATT LED	70
1L075	75 WATT LED	75
1L080	80 WATT LED	80
1L085	85 WATT LED	85
1L090	90 WATT LED	90
1L095	95 WATT LED	95

LED Lighting Fixtures (cont.)		
<u>Device Code</u>	<u>Device Description</u>	<u>Rated Watts</u>
1L110	100 WATT LED	100
1L115	115 WATT LED	115
1L120	120 WATT LED	139
1L125	125 WATT LED	125
1L130	130 WATT LED	130
1L135	135 WATT LED	135
1L140	140 WATT LED	164
1L145	145 WATT LED	145
1L150	150 WATT LED	150
1L155	155 WATT LED	155
1L160	160 WATT LED	160
1L165	165 WATT LED	165
1L170	170 WATT LED	170
1L175	175 WATT LED	175
1L180	180 WATT LED	180
1L185	185 WATT LED	185
1L190	190 WATT LED	190
1L200	200 WATT LED	200
1L210	210 WATT LED	210
1L220	220 WATT LED	220
1L240	240 WATT LED	240

## Proposed Fixture Codes (cont.)

Four Foot T8 HP/RW Systems		
<u>Device Code</u>	<u>Device Description</u>	<u>Rated Watts</u>
1F25EEL	1L4' 25W T8EE/ELEE LPF	19
1F25EEE	1L4' 25W T8EE/ELEE	22
1F25EEH	1L4' 25W T8EE/EELE HPF	30
1F25EEE	1L4' 25W T8EE/ELEE	22
2F25EEL	2L4' 25W T8EE/ELEE LPF	37
2F25EEE	2L4' 25W T8EE/ELEE	43
2F25EEH	2L4' 25W T8EE/EELE HPF	57
3F25EEL	3L4' 25W T8EE/ELEE LPF	57
3F25EEE	3L4' 25W T8EE/ELEE	64
3F25EEH	3L4' 25W T8EE/EELE HPF	86
4F25EEL	4L4' 25W T8EE/ELEE LPF	75
4F25EEE	4L4' 25W T8EE/ELEE	86
4F25EEH	4L4' 25W T8EE/EELE HPF	111
4F25EEL	4L4' 25W T8EE/ELEE LPF	75
1F28EEL	1L4' 28W T8EE/ELEE LPF	22
1F28EEE	1L4' 28W T8EE/ELEE	24
1F28EEH	1L4' 28W T8EE/EELE HPF	33
2F28EEL	2L4' 28W T8EE/ELEE LPF	42
2F28EEE	2L4' 28W T8EE/ELEE	48
2F28EEH	2L4' 28WT8EE/EELE HPF	64
3F28EEL	3L4' 28W T8EE/ELEE LPF	63
3F28EEE	3L4' 28W T8EE/ELEE	72
3F28EEH	3L4' 28W T8EE/EELE HPF	96
4F28EEL	4L4' 28W T8EE/ELEE LPF	83
4F28EEE	4L4' 28W T8EE/ELEE	94
4F28EEH	4L4' 28W T8EE/EELE HPF	126
1F30EEL	1L4' 30W T8EE/ELEE LPF	24
1F30EEE	1L4' 30W T8EE/ELEE	26
1F30EEH	1L4' 30W T8EE/EELE HPF	36
2F30EEL	2L4' 30W T8EE/ELEE LPF	45
2F30EEE	2L4' 30W T8EE/ELEE	52
2F30EEH	2L4' 30WT8EE/EELE HPF	69
3F30EEL	3L4' 30W T8EE/ELEE LPF	68
3F30EEE	3L4' 30W T8EE/ELEE	77
3F30EEH	3L4' 30W T8EE/EELE HPF	103
4F30EEL	4L4' 30W T8EE/ELEE LPF	89
4F30EEE	4L4' 30W T8EE/ELEE	101
4F30EEH	4L4' 30W T8EE/EELE HPF	133
1F30EEL	1L4' 30W T8EE/ELEE LPF	24
1F30EEE	1L4' 30W T8EE/ELEE	26
1F30EEH	1L4' 30W T8EE/EELE HPF	36
2F30EEL	2L4' 30W T8EE/ELEE LPF	45
2F30EEE	2L4' 30W T8EE/ELEE	52
2F30EEH	2L4' 30WT8EE/EELE HPF	69

Four Foot T8 HP/RW Systems (cont.)		
<u>Device Code</u>	<u>Device Description</u>	<u>Rated Watts</u>
3F30EEL	3L4' 30W T8EE/ELEE LPF	68
3F30EEE	3L4' 30W T8EE/ELEE	77
3F30EEH	3L4' 30W T8EE/EELE HPF	103
4F30EEL	4L4' 30W T8EE/ELEE LPF	89
4F30EEE	4L4' 30W T8EE/ELEE	101
4F30EEH	4L4' 30W T8EE/EELE HPF	133
1F32EEL	1L4' T8EE/ELEE LPF	25
1F32EEE	1L4' T8EE/ELEE	28
1F32EEH	1L4' T8EE/ELEE LPF	38
2F32EEL	2L4' T8EE/ELEE LPF	47
2F32EEE	2L4' T8EE/ELEE	53
2F32EEH	2L4' T8EE/ELEE HPF	73
3F32EEL	3L4' T8EE/ELEE LPF	72
3F32EEE	3L4' T8EE/ELEE	82
3F32EEH	3L4' T8EE/ELEE/HPF	109
4F32EEL	4L4' T8EE/ELEE LPF	95
4F32EEE	4L4' T8EE/ELEE	107
4F32EEH	4L4' T8EE/ELEE HPF	141
5F32EEH	5L4' T8EE/ELEE HPF	182
6F32EEH	6L4' T8EE/ELEE HPF	218
8F32EEH	8L4' T8EE/ELEE HPF	282

T5 Systems		
<u>Device Code</u>	<u>Device Description</u>	<u>Rated Watts</u>
1F14SSE	1L2' T5/ELIG	16
1F21SSE	1L3' T5/ELIG	24
1F24HSE	1L2' 24W T5HO/ELIG	29
1F28SSE	1L4' T5/ELIG	32
1F39HSE	1L3' T5 HO/ELIG	42
1F54HSE	1L4' T5 HO/ELIG	59
2F14SSE	2L2' T5/ELIG	34
2F24HSE	2L2' T5HO/ELIG	52
2F21SSE	2L3' T5/ELIG	47
2F28SSE	2L4' T5/ELIG	63
2F39HSE	2L3' T5 HO/ELIG	85
2F54HSE	2L4' T5 HO/ELIG	117
3F54HSE	3L4' T5 HO/ELIG	177
4F54HSE	4L 54W T5 HO	234
5F54HSE	5L4' T5 HO/ELIG	294
6F54HSE	6L 54W T5 HO	351
8F54HSE	8L4' T5 HO/ELIG	468
10F54HSE	10L' 54W T5HO	585